

DMX CHART



www.chauvetprofessional.com

DMX Values

STD.P

Channel	Function	Value	Percent/Setting
1	Dimmer	000 ⇔ 255	0-100%
2	Fine Dimmer	000 ⇔ 255	Fine control (16-bit)
3	Shutter	000 ⇔ 009	No function
		010 ⇔ 099	Slow to fast
		100 ⇔ 109	No function
		110 ⇔ 179	Lightning effect from slow to fast
		180 ⇔ 189	No function
		190 ⇔ 255	Random effect from slow to fast
4	Zoom	000 ⇔ 255	Narrow-wide
5	Zoom Motor Reset	000 ⇔ 200	No function
		201 ⇔ 220	Zoom motor reset
		221 ⇔ 255	No function

DOS

Channel	Function	Value	Percent/Setting
1	Dimmer	000 ⇔ 255	0-100%
2	Fine Dimmer	000 ⇔ 255	Fine control (16-bit)

UNO

Channel	Function	Value	Percent/Setting
1	Dimmer	000 ⇔ 255	0-100%